## GHM Messtechnik GmbH - Location Honsberg

Tenter Weg 2-8 • 42897 Remscheid • Germany Fon +49-2191-9672-0 • Fax -40 www.ghm-messtechnik.de • info@honsberg.com

# GHM-HONSBERG

# **Product Information**

# Switching head A-H1.1

For devices HD1K- HD2K-HD1KO- HD2KO-



- I M1 Ex ia I Ma
- II 1G Ex ia IIC T4 Ga
- II 1D Ex ia IIIC T135°C Da

# **Characteristics**


Intrinsically safe switching head with reed switch and ATEX approval, for the HD range of devices, for use in intrinsically safe power circuits.

# **Technical data**

pi-ho\_ze-a-h1\_e V1.02-01

Switch	reed switch	
Medium	-20+120 °C	
temperature		
Ambient	-20+50 °C	
temperature		
Weight	0.5 kg additionally	
without signal lam		
Wiring	transformer No. 0.213	
Switching voltage	max. 30 V	
Switching current	max. 1.5 A	
Switch performance	max. 50 W	
with signal lamp		
Wiring	Transformer with signal lamp No. 0.208	
Switching voltage	max. 15 V, 28 V or 36 V	
Switching current	max. 1.5 A	
Switch performance	max. 50 W	
Protection class	3 - Protective extra low voltage	
Ingress protection	IP 65	
Electrical connection	cable 2.5 m, other cable lengths up to max. 5 m are optionally available	

### **Dimensions**



# Handling and operation

### Note

#### ΑII

- For use only in intrinsically safe power circuits provide a suitable isolating amplifier.
- Cable lengths max. 5 m.
- It must be ensured that the values given for voltage, current, and power are not exceeded.
- When switched on, a load must be connected in series.
- The electrical details apply to ohmic loads. Capacitive, inductive and lamp loads must be operated using a protective circuit.

# HD1KO- / HD2KO-

 Display with plastic parts - do not open in an explosive atmosphere.

### **Adjustment**

If it is necessary to set the switching value, the switching head can be adjusted lengthways. When the switching value is reached, the switching unit is fixed in place by a fastening bolt.



# Ordering code

The basic device is ordered e.g. HD1K-015GM005A with Switching head e.g. A-H1.1-1.

1.	Wiring - switching voltage	
	1	wiring no. 0.213 - 30 V
	2	wiring no. 0.208 - 15 V
	3	wiring no. 0.208 - 28 V
	4	wiring no. 0.208 - 36 V

.. professional Instruments "MADE IN GERMANY"